



ATC-AMFM2

Dual AM/FM Tuner Card for Adagio

- [Product Description](#)
- [Product Resources](#)
- [Technical Specifications](#)



Product Description

ATC-Series tuner cards are designed for use with Adagio systems that feature tuner card slots. The ATC-AMFM2 provides two (2) fully independent AM/FM tuners on a single card.

Product Resources

[Cad Files \(ZIP\)](#)

Technical Specifications

Audio	
Output Level	1 Vrms @ 1kHz
FM Tuner (Typical of 2)	
Frequency Range	87.50 to 108 MHz (50 or 100 kHz steps)
Intermediate Frequency	10.7 MHz
Usable Sensitivity	11 dBf mono
S/N Ratio	64dB @ 65 dBf mono; 60dB @ 65 dBf stereo
IF Rejection	100dB
AM Rejection	55dB
Stereo Separation	40dB
AM Tuner (Typical of 2)	

Frequency Range	530 to 1710 kHz (9 or 10 kHz steps)
Sensitivity	3.5 μ V (RF input level 10dB S+N/N)
Selectivity	10 kHz
Alternate Channel Selectivity	55dB
Image Rejection	35dB
IF Rejection	60dB

Connectors

AM ANT A – B	(2) 2-pin spring-loaded terminals; Connect to AM loop antennas (included); Impedance: 50 ohms
FM ANT A – B	(2) F-type coaxial; Connect to T-type FM antennas (included); Impedance: 75 ohms

Printed from URL:

http://www.crestron.com/products/show_products.asp?type=commercial&cat=1011&subcat=1291&id=1465



faircom media GmbH • Biggestr.43 • D-57462 Olpe
Tel.: +49 (0) 2761 8396 0 • Fax: +49 (0) 2761 8396 70
info@faircom-media.de • www.faircom-media.de